

FortiAnalyzer - Release Notes

Version 6.2.10

FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO GUIDE

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

NSE INSTITUTE

<https://training.fortinet.com>

FORTIGUARD CENTER

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



February 28, 2023

FortiAnalyzer 6.2.10 Release Notes

05-6210-881376-20230228

TABLE OF CONTENTS

Change Log	5
FortiAnalyzer 6.2.10 Release	6
Supported models	6
Special Notices	7
Newly deployed, factory reset, or disk format may trigger upgrade code on subsequent reboot	7
Maximum ADOM limits for FortiAnalyzer	7
Port 8443 reserved	7
All OFTP connections must be encrypted for FortiAnalyzer 6.2.0 (or higher)	7
Hyper-V FortiAnalyzer-VM running on an AMD CPU	8
SSLv3 on FortiAnalyzer-VM64-AWS	8
Pre-processing logic of ebtime	8
Upgrade Information	9
Downgrading to previous versions	9
Firmware image checksums	9
FortiAnalyzer VM firmware	10
SNMP MIB files	11
Product Integration and Support	12
FortiAnalyzer version 6.2.10 support	12
Web browsers	12
FortiOS/FortiOS Carrier	13
FortiAnalyzer	13
FortiAuthenticator	13
FortiCache	13
FortiClient	13
FortiDDoS	14
FortiMail	14
FortiManager	14
FortiProxy	14
FortiSandbox	14
FortiSwitch ATCA	14
FortiWeb	15
Virtualization	15
Feature support	15
Language support	16
Supported models	17
FortiGate models	17
FortiCarrier models	20
FortiDDoS models	21
FortiAnalyzer models	22
FortiMail models	23
FortiSandbox models	23
FortiSwitch ATCA models	24

FortiWeb models	24
FortiCache models	26
FortiProxy models	26
FortiAuthenticator models	26
Appendix A - Recommended maximum number of ADOMs supported	27

Change Log

Date	Change Description
2023-02-28	Initial release of 6.2.10.

FortiAnalyzer 6.2.10 Release

This document provides information about FortiAnalyzer version 6.2.10 build 1496.



The recommended minimum screen resolution for the FortiAnalyzer GUI is 1920 x 1080. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 6](#)

Supported models

FortiAnalyzer version 6.2.10 supports the following models:

FortiAnalyzer	FAZ-200F, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000E, FAZ-1000F, FAZ-2000E, FAZ-3000E, FAZ-3000F, FAZ-3000G, FAZ-3500E, FAZ-3500G, FAZ-3500F, FAZ-3700F and FAZ-3900E.
FortiAnalyzer VM	FAZ-VM64, FAZ-VM64-Ali, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-GCP, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).

Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 6.2.10.

Newly deployed, factory reset, or disk format may trigger upgrade code on subsequent reboot

For a newly deployed VM instance or appliance, a disk format or a factory reset on a FortiAnalyzer unit running version 6.2.3 may trigger the upgrade code upon rebooting the system, which in turn may update the database configuration, although no upgrades are required. This issue does not affect FortiAnalyzer units upgraded from versions prior to 6.2.3.

Workaround: Immediately after deploying a new FortiAnalyzer with version 6.2.3, reboot the system before administering any configuration.

Maximum ADOM limits for FortiAnalyzer

FortiAnalyzer hardware devices and VMs display a warning when the recommended maximum number of ADOMs is reached or exceeded. The platform does not enforce the limit; however, adding more ADOMs may affect the performance of the unit. For more details, see [Appendix A - Recommended maximum number of ADOMs supported on page 27](#).

Port 8443 reserved

Port 8443 is reserved for https-logging from FortiClient EMS for Chromebooks.

All OFTP connections must be encrypted for FortiAnalyzer 6.2.0 (or higher)

Prior to upgrading to FortiAnalyzer 6.2, make sure that all FortiGate devices are configured to use encryption when communicating with FortiAnalyzer. Starting with FortiAnalyzer 6.2.0, all OFTP communications must be encrypted.

Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol tlsv1
end
```

Pre-processing logic of ebtime

Logs with the following conditions met are considered usable for the calculation of estimated browsing time:

Traffic logs with `logid` of 13 or 2, when `logid == 13`, `hostname` must not be empty. The `service` field should be either `HTTP`, `80/TCP` or `443/TCP`.

If all above conditions are met, then `devid`, `vdom`, and `user` (`srcip` if `user` is empty) are combined as a key to identify a user. For time estimation, the current value of `duration` is calculated against history session start and end time, only un-overlapped part are used as the `ebtime` of the current log.

Upgrade Information

You can upgrade FortiAnalyzer 6.0.3 or later directly to 6.2.10.



For other upgrade paths and details about upgrading your FortiAnalyzer, see *FortiAnalyzer Upgrade Guide*.



Upgrading to FortiAnalyzer 6.0.2 from 6.0.0 or 6.0.1 is supported and does not trigger a log database rebuild.

This section contains the following topics:

- [Downgrading to previous versions on page 9](#)
- [Firmware image checksums on page 9](#)
- [FortiAnalyzer VM firmware on page 10](#)
- [SNMP MIB files on page 11](#)

Downgrading to previous versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release via the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrading process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset all-settings
execute format {disk | disk-ext4}
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. To verify the integrity of the download, select the *Checksum* link next to the *HTTPS* download link. A dialog box will be displayed with the image file name and checksum code. Compare this checksum with the checksum of the firmware image.

FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Aliyun

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Disk (VHD), and OVF files.

Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `FAZ_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Azure.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `FAZ_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

VMware ESX/ESXi

- `.out`: Download either the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information see the FortiAnalyzer product data sheet available on the Fortinet web site, <https://www.fortinet.com/products/management/fortianalyzer.html>. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer v5.00 file folder.

Product Integration and Support

This section lists FortiAnalyzer 6.2.10 support of other Fortinet products. It also identifies what FortiAnalyzer features are supported for log devices and what languages FortiAnalyzer GUI and reports support. It also lists which Fortinet models can send logs to FortiAnalyzer.

The section contains the following topics:

- [FortiAnalyzer version 6.2.10 support on page 12](#)
- [Feature support on page 15](#)
- [Language support on page 16](#)
- [Supported models on page 17](#)

FortiAnalyzer version 6.2.10 support

This section identifies FortiAnalyzer version 6.2.10 product integration and support information:

- [Web browsers on page 12](#)
- [FortiOS/FortiOS Carrier on page 13](#)
- [FortiAnalyzer on page 13](#)
- [FortiAuthenticator on page 13](#)
- [FortiCache on page 13](#)
- [FortiClient on page 13](#)
- [FortiDDoS on page 14](#)
- [FortiMail on page 14](#)
- [FortiManager on page 14](#)
- [FortiProxy on page 14](#)
- [FortiSandbox on page 14](#)
- [FortiSwitch ATCA on page 14](#)
- [FortiWeb on page 15](#)
- [Virtualization on page 15](#)



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Web browsers

This section lists FortiAnalyzer version 6.2.10 product integration and support for web browsers:

- Microsoft Edge 80 (80.0.361 or later)
- Mozilla Firefox version 88

- Google Chrome version 90

FortiOS/FortiOS Carrier

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiOS/FortiOS Carrier:

- 6.2.0 and later
- 6.0.0 and later
- 5.6.0 and later
- 5.4.0 and later

FortiAnalyzer

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiAnalyzer:

- 6.2.0 and later
- 6.0.0 and later
- 5.6.0 and later
- 5.4.0 and later

FortiAuthenticator

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiAuthenticator:

- 6.0 and later
- 5.0 to 5.5
- 4.3

FortiCache

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiCache:

- 4.2.9
- 4.1.6
- 4.0.4

FortiClient

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiClient:

- 6.2.1 and later
- 6.0.0 and later
- 5.6.0 and later
- 5.4.0 and later

When using FortiClient with FortiAnalyzer, it is recommended to upgrade both to their latest versions. The versions between the two products should match. For example, if using FortiAnalyzer 6.2.9, use FortiClient 6.2.9.

FortiDDoS

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiDDoS:

- 5.3.0 and later
- 5.2.0 and later
- 5.1.0 and later

FortiMail

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiMail:

- 6.2.7
- 6.0.10
- 5.4.10
- 5.3.13

FortiManager

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiManager:

- 6.2.0 and later
- 6.0.0 and later
- 5.6.0 and later
- 5.4.0 and later

FortiProxy

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiProxy:

- 1.0

FortiSandbox

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiSandbox:

- 3.1.0
- 3.0.5
- 2.5.2
- 2.4.1
- 2.3.3
- 2.2.2

FortiSwitch ATCA

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiSwitch ATCA:

- 5.0.0 and later

FortiWeb

This section lists FortiAnalyzer version 6.2.10 product integration and support for FortiWeb:

- 6.2.4
- 6.1.1
- 6.0.5
- 5.9.1
- 5.8.6
- 5.7.2
- 5.6.1
- 5.5.6
- 5.4.1

Virtualization

This section lists FortiAnalyzer version 6.2.10 product integration and support for virtualization:

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Citrix XenServer 7.2
- Linux KVM Redhat 7.1
- Microsoft Azure
- Microsoft Hyper-V Server 2012 and 2016
- OpenSource XenServer 4.2.5
- VMware ESXi versions 5.0, 5.5, 6.0, 6.5 and 6.7

Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiAnalyzer	✓		✓	
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiGate	✓	✓		✓

Platform	Log View	FortiView	Event Management	Reports
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiMail	✓		✓	✓
FortiManager	✓		✓	
FortiProxy	✓		✓	✓
FortiSandbox	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	✓

Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French		✓
Hebrew		✓
Hungarian		✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓
Russian		✓
Spanish		✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language from the drop-down list. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiAnalyzer, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiAnalyzer. For more information, see the *FortiAnalyzer Administration Guide*.

Supported models

This section identifies which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch, FortiWeb, FortiCache, and FortiProxy models and firmware versions can send logs to a FortiAnalyzer appliance running version 6.2.10. Please ensure that the log devices are supported before completing the upgrade.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 17](#)
- [FortiCarrier models on page 20](#)
- [FortiDDoS models on page 21](#)
- [FortiAnalyzer models on page 22](#)
- [FortiMail models on page 23](#)
- [FortiSandbox models on page 23](#)
- [FortiSwitch ATCA models on page 24](#)
- [FortiWeb models on page 24](#)
- [FortiCache models on page 26](#)
- [FortiProxy models on page 26](#)
- [FortiAuthenticator models on page 26](#)

FortiGate models

Model	Firmware Version
FortiGate: FortiGate-30E, FortiGate-30E-3G4G-GBL, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60E, FortiGate-60F, FortiGate-61F, FortiGate-60E-POE, FortiGate-61E, FortiGate-80D, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-100D, FortiGate-100E, FortiGate-100F, FortiGate-101F, FortiGate-100F, FortiGate-101E, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-201E, FortiGate-200F, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FG-400E, FG-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-3400E, FortiGate-3401E, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F	6.2

Model	Firmware Version
FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6300F, FortiGate-6301F, FortiGate-6500F, FortiGate-6501F FortiGate 7000 Series: FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7121F FortiCarrier-7000 series: FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7121F FortiGate DC: FortiGate-80C-DC, FortiGate-600C-DC, FortiGate-800C-DC, FortiGate-800D-DC, FortiGate-1000C-DC, FortiGate-1500D-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3240C-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-DC, FortiGate-3980E-DC FortiGate Hardware Low Encryption: FortiGate-80C-LENC, FortiGate-600C-LENC, FortiGate-1000C-LENC FortiWiFi: FortiWiFi-30D, FortiWiFi-30D-POE, FortiWiFi-30E, FortiWiFi-30E-3G4G-INTL, FortiWiFi-30E-3G4G-NAM, FortiWiFi-50E, FortiWiFi-50E-2R, FortiWiFi-51E, FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-61E, FortiWiFi-60F, FortiWiFi-61F, FortiWiFi-80CM, FortiWiFi-81CM, FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL FortiGate-VM: FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-Xen, FortiGate-VMX-Service-Manager FortiGate Rugged: FortiGateRugged-30D, FortiGateRugged-30D-ADSL-A, FortiGateRugged-35D, FortiGateRugged-60F, FortiGateRugged-60F-3G4G FortiOS: FortiOS-VM64, FortiOS-VM64-HV, FortiOS-VM64-KVM, FortiOS-VM64-Xen	
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-GBL, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-40F, FG-40F-3G4G, FG-41F, FG-41F-3G4G, FG-50E, FG-51E, FG-52E, FG-60D, FG-60F, FG-60D-POE, FG-60E, FG-60E-POE, FG-60F, FG-61E, FG-70D, FG-70D-POE, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100F, FG-100F, FG-101F, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG300D, FG-300E, FG-301E, FG-400D, FG-400E, FG-401E, FG-500D, FG-500E, FG-501E, FG-600D, FG-600E, FG-601E, FG-800D, FG-900D, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-1800F, FG-1801F, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3400E, FG-3401E, FG-3600E, FG-3601E, FG-3700D, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E, FG-2200E, FG-2201E, FG-3300E, FG-3301E, FG-1100E, FG-1101E, FG-3400E, FG-3401E, FG-3400E-DC, FG-3401E-DC FortiGate 5000 Series: FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E, FG-7040E, FG-7060E, FG-7060E-8-DC	6.0

Model	Firmware Version
FortiGate DC: FG1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC FortiGate Hardware Low Encryption: FG-100D-LENC, FG-600C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-40F, FWF-40F-3G4G, FWF-41F, FWF-41F-3G4G, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FW-60E-DSL, FW-60E-DSLJ, FWF-60F, FWF-61F, FWF-61E, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-AZUREONDEMAND, FG-VM64-Azure, FG-VM64-GCP, VM64-GCPONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D	
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSLJ, FG-60E-POE, FG-60E-DSL, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100F, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG-300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E, FG-7040E, FG-7060E, FG-7060E-8-DC FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC, FG-7060E-8-DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FW-60E-DSL, FW-60E-DSLJ, FWF-60D-POE, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-Azure, FG-VM64-AZUREONDEMAND, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOSVM64, FOSVM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D	5.6

Model	Firmware Version
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSL, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100F, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-200E, FG-201E, FGT-300D, FGT-300E, FGT-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E, FG-2000E, FG-2500E FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E-Q, FG-7030E-S, FG-7040E-1, FG-7040E-2, FG-7040E-3, FG-7040E-4, FG-7040E-5, FG-7040E-6, FG-7040E-8, FG-7040E-8-DC, FG-7060E-1, FG-7060E-2, FG-7060E-3, FG-7060E-4, FG-7060E-5, FG-7060E-6, FG-7060E-8 (Update only) FortiGate 7000 series: FG-7030E, FG-7040E, FG-7060E, FG-7060E-8-DC FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815DC, FG-7060E-8-DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E-DSL, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM FortiGate Rugged: FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	5.4

FortiCarrier models

Model	Firmware Version
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-6000 series: FortiCarrier-6300F, FortiCarrier-6301F, FortiCarrier-6500F, FortiCarrier-6501F FortiCarrier-7000 series: FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7121F	6.2

Model	Firmware Version
FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3700D, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001D, FGT-5001E FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC FortiGate 6000 series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 series: FG-7030E, FG-7040E, FG-7060E, FG-7060E-8-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	6.0
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001C, FGT-5001D, FGT-5001E FortiCarrier 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiCarrier 7000 Series: FG-7030E, FG-7040E, FG-7060E, FG-7060E-8-DC FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC, FGT-7060E-8-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	5.6
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FG-3600E, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-5001C, FGT-5001D, FGT-7030E, FGT-7040E FortiCarrier 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiCarrier 7000 Series: FG-7030E, FG-7040E, FG-7060E, FG-7060E-8-DC FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-7060E-8-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	5.4

FortiDDoS models

Model	Firmware Version
FortiDDoS: FI-200B, FI-400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-1500B, FI-2000B, FI-2000E	5.1

Model	Firmware Version
FortiDDoS: FI-1500E, FI-2000E	5.0
FortiDDoS: FI-200B, FI-400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-2000B	4.0, 4.1, 4.2, 4.3, 4.4, 4.5, 4.7

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FAZ-200F, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000E, FAZ-2000E, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3700F and FAZ-3900E.	6.2
FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-Ali, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-GCP, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	
FortiAnalyzer: FAZ-200D, FAZ-200F, FAZ-300D, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000D, FAZ-1000E, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3700F and FAZ-3900E.	6.0
FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-ALI, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-GCP, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, and FAZ-3900E.	5.6
FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, and FAZ-4000B.	5.4
FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-XEN (Citrix XenServer and Open Source Xen), FAZ-VM64-KVM, and FAZ-VM64-AWS.	
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-200E, FAZ-300D, FAZ-400C, FAZ-400E, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, FAZ-4000B	5.2
FortiAnalyzer VM: FAZ-VM, FAZ-VM-AWS, FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-200E, FAZ-300D, FAZ-400B, FAZ-400C, FAZ-400E, FAZ-1000B, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000A, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-4000A, FAZ-4000B	5.0
FortiAnalyzer VM: FAZ-VM, FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM-KVM, FAZ-VM-XEN	

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200D, FE-200E, FE-400E, FE-1000D, FE-2000E, FE-3000D, FE-3000E, FE-3200E, FE-VM, FML-200F, FML-400F, FML-900F	6.2
FortiMail: FE-60D, FE-200D, FE-200E, FE-400E, FE-1000D, FE-2000E, FE-3000D, FE-3000E, FE-3200E, FE-VM, FML-200F, FML-400F, FML-900F	6.0
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000E, FE-3200E FortiMail Low Encryption: FE-3000C-LENC	5.4
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000D, FE-3000E, FE-3200E, FE-5002B FortiMail Low Encryption: FE-3000C-LENC FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.3
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5002B FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.2
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.1
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-1000D, FE-2000A, FE-2000B, FE-3000C, FE-3000D, FE-4000A, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.0

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox-VM: FSA-AWS, FSA-VM	3.1
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-AWS, FSA-VM	3.0
FortiSandbox VM: FSA-KVM, FSA-VM	2.5.2
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-VM	2.4.1 2.4.0 2.3.3 2.3.2

Model	Firmware Version
FortiSandbox: FSA-1000D, FSA-3000D, FSA-3500D	2.2.2
FortiSandbox VM: FSA-VM	2.1.3
FortiSandbox: FSA-1000D, FSA-3000D	2.0.3
FortiSandbox VM: FSA-VM	1.4.2
FortiSandbox: FSA-1000D, FSA-3000D	1.4.1
	1.3.0
	1.2.0 and later

FortiSwitch ATCA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5902D, FTCL-5903C, FTCL-59	5.2.0
FortiSwitch-ATCA: FS-5003A, FS-5003B	5.0.0
FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3.0
	4.2.0

FortiWeb models

Model	Firmware Version
FortiWeb: FortiWeb-400C, FortiWeb-3000C, FortiWeb-4000C, FortiWeb-3000CFSX, FortiWeb-100D, FortiWeb-400D, FortiWeb-600D, FortiWeb-1000D, FortiWeb-3000D, FortiWeb-4000D, FortiWeb-3000DFSX, FortiWeb-400E, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-3000E, FortiWeb-3010E, FortiWeb-4000E	6.3
FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	
FortiWeb: FortiWeb-400C, FortiWeb-3000C, FortiWeb-4000C, FortiWeb-3000CFSX, FortiWeb-100D, FortiWeb-400D, FortiWeb-600D, FortiWeb-1000D, FortiWeb-3000D, FortiWeb-4000D, FortiWeb-3000DFSX, FortiWeb-400E, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-3000E, FortiWeb-3010E, FortiWeb-4000E	6.2
FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	
FortiWeb: FortiWeb-400C, FortiWeb-3000C, FortiWeb-4000C, FortiWeb-3000CFSX, FortiWeb-100D, FortiWeb-400D, FortiWeb-600D, FortiWeb-1000D, FortiWeb-3000D, FortiWeb-4000D, FortiWeb-3000DFSX, FortiWeb-400E, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-3000E, FortiWeb-3010E, FortiWeb-4000E	6.1

Model	Firmware Version
FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	
FortiWeb: FWB-100D, FWB-400C, FWB-400D, FWB-600D, FWB-1000D, FWB-1000E, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM, FWB-HYPERV, FWB-XENOPEN, FWB-XENSERVR	6.0.1
FortiWeb: FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.9.1
FortiWeb: FWB-1000C, FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-Azure-Ondemand, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.8.6
FortiWeb: FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-OS1, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.7.2
FortiWeb: FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.6.1
FortiWeb: FWB-100D, FWB-400C, FWB-400D, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM-64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV, FWB-KVM, FWB-AZURE	5.5.6
FortiWeb: FWB-100D, FWB-400C, FWB-1000C, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV	5.4.1

Model	Firmware Version
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, and FWB-HYPERV	5.3.9
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-HYPERV, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR	5.2.4

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3000E, FCH-3900E FortiCache VM: FCH-VM64, FCH-KVM	4.0, 4.1, 4.2

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-2000E, FPX-4000E FortiProxy VM: FPX-KVM, FPX-VM64	1.0/1.1

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E FortiAuthenticator VM: FAC-VM	6.0 to 6.3
FortiAuthenticator: FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000B, FAC-3000D, FAC-3000E FortiAuthenticator VM: FAC-VM	5.0 to 5.5
FortiAuthenticator: FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000B, FAC-3000D, FAC-3000E FortiAuthenticator VM: FAC-VM	4.3

Appendix A - Recommended maximum number of ADOMs supported

FortiAnalyzer supports a recommended number of ADOMs based on the version.

Recommended maximum number of ADOMs supported for hardware versions:


FortiAnalyzer Platform	Maximum number of ADOMs
Desktop models	1
200F/300F/400F	25
800F/ 1000 Series	50
2000 Series	250
3000 Series	500
3700F and higher	800

Recommended maximum number of ADOMs supported for VMs:

FortiAnalyzer Platform	Maximum number of ADOMs
FAZ-VM-BASE (1 GB/Day)	5
1 GB/Day < License <= 5 GB/Day	10
5 GB/Day < License <= 25 GB/Day	25
25 GB/Day < License <= 100 GB/Day	50
100 GB/Day < License <= 500 GB/Day	250
500 GB/Day < License <= 1000 GB/Day	500
1000 GB/Day < License <= 5000 GB/Day	800
License > 5000 GB/Day	1100



FORTINET®



Copyright© 2023 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.